Design of S-Shape GPS Application Electrically Small Antenna

Riki H. Patel, Arpan Desai, Trushit Upadhyaya, Shobhit K. Patel

Abstract— The microstrip antennas area has seen some inventive work in recent years and is now one of the most dynamic fields of antenna theory. A novel and simple wideband monopole antenna is presented printed on a single dielectric substrate which is fed by a 50 ohm microstrip line having a low-profile antenna structure with two parallel s-shaped meandered line of same size. This antenna is fed by a coaxial feeding tube.

In this research, S-form microstrip patch antenna is designed from measuring the prototypes of the proposed antenna one available bands with 10db return loss bandwidths of about GPS application (GPS L2 1490 MHz) and covering the 1400 to 1580 MHz frequency band at 1.5 GHz, the simulated results for main parameters such as return loss, impedance bandwidth, radiation patterns, and gains are also discussed herein. The modeling study shows that such antennas, in simplicity design and supply, can satisfy GPS application. Two parallel slots are incorporated to disturb the surface flow path, introducing local inductive effect. This antenna is fed by a coaxial feeding tube.

Keywords—Bandwidth, electrically small antenna, microstrip patch antenna, GPS.

I. INTRODUCTION

A MICROSTRIP patch antenna comprises a dielectric substrate, with a ground plane on the other side. Because of its advantages such as light weight, low profile flat configuration, lower manufacturing cost and the ability to integrate with microwave integrated circuit technology, the microstrip patch antenna is well suited for applications as the wireless communication system, GPS, cell phones, pagers, radar and satellite communications systems. [21]-[23].

The development of small antennas integrated plays an important role in the progress of the rapid expansion applications of military and commercial communications. High-speed wireless promises to make interactive, data, and video services available voice anytime anywhere. The technology to support these applications has made possible by recent advances in high-density RF and the microwave circuit packaging. [24]-[27] System requirements for faster data transmission in compact designs lighter drive technology area, increasing design solutions often Great designs require integration density microwave devices, circuits and radiating

Riki H Patel is with the Chandubhai S. Patel Institute of Technology Charusat University, Changa (Gujarat), India (phone: +91-9662323379; e-mail: rikipatel.ec@charusat.ac.in).

Arpan Desai, is with the Chandubhai S. Patel Institute of Technology, Charusat University, Changa (Gujarat), India.

Trushit Upadhyaya and Shobhit K. Patel are with the Electronic and Communication Engineering Department, Charotar University of Science & Technology, Changa, Gujarat, India, (e-mail: trushitupadhyaya.ec @charusat.ac.in, shobhitpatel.ec@charusat.ac.in).

elements that offer light weight, small size, and optimum performance. [1]-[3] During the last two decades, microstrip patch antenna has received considerable attention for use in staff communication systems and synthetic aperture radar applications because of their compactness among other advantages. Intensive research has been carried out with develop new techniques to overcome the patch microstrip [4]-[7] antennas drawbacks, the most restrictive to be narrowband. Increasing bandwidth and return loss improved without increasing the size of the antenna and production process is important to apply this antenna to Modern mobile communications systems and need to be carried out. Many applications in communications and radars require double circular or linear polarization, and flexibility provided by microstrip antenna technology has led to a wide variety of designs and techniques to fill this need [8], [9]. In recent years, demand for compact mobile phone terminals has grown. Phones with the size of a pocket have begun to appear on the market, as demand for increase in the electron mobility increases, the need for small phones will most likely increase. A small antenna size is required as one of the important factors in portable mobile communication systems. The Micro-strip Patch Antennas (MPA) is widely used due to its low volume and Features thin profile. MPA size is basically determined by its length and width resonance. Reduction patch size can be achieved by using patches substrate material with high permittivity and small substrate height [10], [11]. However, in this case, the low radiation efficiency reduces the gain of the antenna.

In this study, a patch antenna S as a novel optimized for simplicity in design and proposed power. We have a feature that also meets the application of GPS system. Antenna parameters, such as return loss, impedance bandwidth, radiation patterns and gains are treated in this paper [12], [13].

II. S-SHAPED PATCH SMALL ANTENNA ANALYSIS

The results of the development of a wideband radiator for use in applications of wireless communications are presented in this section [14], [15]. Bandwidth is specified as frequency band in which the return loss is less than -10 dB.

The proposed geometry of the microstrip patch antenna as shown in S-shape Fig. 1. The proposed antenna is loaded with two notches. The design specification of the antenna is given in Table I.

First the conventional patch length and width is designed. After designing the patch, we have taken out two slits from the patch to make it S-shape patch. Basic length and width are designed with the use of following equations [16]-[18].



Fig. 1 S-shape top view design

Width of the patch can be designed using the equation:

$$w = \frac{c}{2f_0\sqrt{\frac{\varepsilon_r + 1}{2}}} \tag{1}$$

where \mathcal{E}_r = relative permittivity, f_0 = center frequency, C= speed of light.

$$L_{eff} = \frac{c}{2f_0 \sqrt{\varepsilon_{reff}}}$$
(2)

$$\varepsilon_{reff} = \frac{\varepsilon_r + 1}{2} + \frac{\varepsilon_r + 1}{2} \left(\frac{1}{\sqrt{1 + 12t}}\right)$$
(3)

$$\Delta L = 0.412t \frac{(\varepsilon_{reff} + 0.3)(\frac{w}{t} + 0.264)}{(\varepsilon_{reff} - 0.258)(\frac{w}{t} + 0.8)}$$
(4)

$$L = L_{eff} - 2\Delta L \tag{5}$$

where t = thickness of the substrate. Here, (2)-(5) using at design the length of the patch. We used the total of the equation having designed the electrically small antenna in S-shape design of GPS application. Here, we have designed the rectangular patch, so length and width are different. We have taken out two slit from the patch to make it S-shape and to improve the results as shown in Fig. 1. Top view of the design is shown in Fig. 1.

Table I shows details about the material. Patch is of the

copper material. The substrate is of Rogers RT/duroid 5870 (tm) material with $\mathcal{E}_r = 2.3$. The base material is also of copper [19], [20].

	TABLE I Dimension List	
Length of the rectangular patch (L)		39.69 mm
Width of the rectangular patch (W)		30.78 mm
Substrate Thickness		3.5 mm
Dielectric constant of the material		2.3
TABLE II		
MATERIAL LIST		
Material		
Patch	Copper	
Substrate	Substrate Rogers RT/duroid 5870 (tm)	

III. SIMULATION RESULTS AND DISCUSSIONS

For simulation, we used HFSS 15 of Ansoft, which is an excellent simulator for RF antennas. After simulating the design, the result we got is as follows.

Fig. 2 shows the Return Loss (S_{11}) plot of the design and Table II shows values of Return Loss (S_{11}) in dB for single bands with their frequency. The minimum return loss that we are getting for this design is -30 dB for the one band centered around 1.500 GHz.



VSWR plot of the design in Fig. 3 shows the values of VSWR for different frequencies. For the whole range VSWR less than 2 and at frequency 1490 MHz and its value at that

less than 2 and at frequencies. For the whole range VSWR for different frequency 1490 MHz and its value at that point is 1.47. Fig. 4 shows the radiation pattern for frequency 1490 MHz for all the phi values for gain 10.48 db values. Fig. 5 shows the polar plot for frequency 1480 MHz for all the phi values for gain values.



Fig. 3 Return Loss (S11) parameter of the antenna VSWR



Fig. 4 Radiation pattern of S- shape ESA GPS antenna



Fig. 5 Polar plot of S- shape ESA GPS antenna

IV. CONCLUSION

Microstrip antennas have become a rapidly growing area of research. Their potential applications are limitless, because of their light weight, compact size, and ease of manufacturing. The low profile S-shape patch is presented in this paper. Simulations and results of the S-shape microstrip patch antenna have provided a useful design for an antenna operating at the frequency of 1480.5 MHz for the GPS applications. The reflection coefficient is below -10 dB from 1400 MHz to 1580 MHz. At the same time, the antenna is thin and compact with the use of low dielectric constant substrate material, and this antenna is electrically small antenna and compact antenna, and small weight antenna.

References

- G. A. Deschamps "Microstrip microwave antennas," 3rd USAF Symposium on Antennas, 1953.
- [2] J. Q. Howell "Microstrip antennas," *IEEE Antenna Propag Soc Int Symp*, Vol. 20 pp. 177–18, 1980.
- [3] R. C. Filho, J. H. ra o, R. A. Martins, A. G. D'Assuncao, L. M. Mendonca, "Simulated and measured results for a S-shaped monopole patch antenna on a BiNbO4 layer", 14th Biennial IEEE Conference on Electromagnetic Field Computation (CEFC),2010.
- [4] A. A. Deshmukh, K. P. Ray, "nalysis of Broadband Psi (Ψ)-Shaped Microstrip ntennas", *IEEE Trans Antennas Propagation Magazine*, Vol. 55, pp. 107-123, 2013.
- [5] O. Hoseini Izadi, M. Mehrparvar," A compact microstrip slot antenna with novel E-shaped coupling aperture", *5th International Symposium* on *Telecommunications(IST)*, pp 110–114, 2010.
- [6] Chae-Hyun Jung; Sang-Ho Lim; Noh-Hoon Myung, "nalysis of an Hshape cross slotted aperture-coupled microstrip patch antenna," Asia Pacific Microwave Conference APMC, pp 1890 – 1893, 2009.
- [7] S. C. Gao, L. W. Li, M. S. Leongand, T. S. Yeo, "FDTD analysis of a compact H-shaped microstrippatch antenna," IEEE Trans Antenna Propogation, pp 494 – 497, Vol.1,2001.
- [8] JM. T. Ali, N. Nordin, I. Pasya, M. N. Md Tan, "H-shaped microstrip patch antenna using L-probe fed for wideband applications", 6th European Conference on Antennas and Propagation (EUCAP), pp. 2827 – 2831, 2012.
- [9] Mingqiang Bai; Jun Xing; Zhigang Wang; Bo Yan, "Design of an Hshape cross slotted aperture-coupled microstrip patch antenna", *IEEE Int. Workshop Electromagnetics Applications Student Innovation* (*iWEM*), pp. 1 – 3, 2012.
- [10] W. Afzal, U. Rafique, M. M. Ahmed, M. A. Khan, F. A. Mughal, "triband H-shaped microstrip patch antenna for DCS and WLAN applications," 19th Int. Conf. Microwave Radar and Wireless Communications (MIKON), Vol. 1, pp 256 – 258, 2012.
- [11] J. Anguera, L. Boada, C. Puente, C. Borja, J. Soler, "Stacked H shaped microstrip patch antenna," IEEE Trans. Antennas Propagation, Vol. 52, Issue 4, pp 983 - 99, 2004.
- [12] C. L. Mak, K. M. Luk, K. F. Lee, Y. L. Chow,"Experimental study of a microstrip patch antenna with an L-shaped probe" IEEE Trans. Antennas Propagation, Vol. 48, Issue 5, pp. 777 – 783, 2000.
- [13] Tingqiang Wu, Hua Su, Liyun Gan, Huizhu Chen, Jingyao Huang, Huaiwu Zhang,"A Compact and Broadband Microstrip Stacked PatchAntenna With Circular Polarization for 2.45-GHz Mobile RFID Reader", IEEE Lett. Antennas and Wireless Propagation, Vol 12, pp 623 - 626,2013.
- [14] I. J.Bahal, and P. Bhartia, *Microstrip Antennas*, Boston, MA, Artech House, 1985.
- [15] V. K. Pandey, and B. R. Vishvakarma, "Theoretical analysis of linear array antenna of stacked patches," Indian J Radio & space phys, Vol. 3, pp.125-127, 2005.
- [16] M. K. Meshram, and B. R. Vishvakarma, "Gap-coupled microstrip array antenna for wide band operation," Int J Electronics, Vol. 88, pp.1161-1175, 2001.
- [17] E. Wang, J. Zheng, Y. Liu," novel dualband patch antenna for WLAN communication," PIER C, Vol. 6, pp.289-291, 2009.
- [18] I. J. Bahl and P. Bhartia, Microstrip Antennas. Dedham, MA: Artech House, 1980.
- [19] P. L. Sullivan and D. H. Schaubert, "Analysis of an aperture coupled rnicrostrip antenna," IEEE Trans. Antennas Propagat., vol. AP-34, pp. 977-984, Aug. 1986.
- [20] H. Kirschning and R. H. Jansen, "Accurate model for effective dielectric constant of microstrips with validity up to millimeter-wave frequencies," Electron. Lett., vol. 18, pp. 272-273, 1982.

International Journal of Electrical, Electronic and Communication Sciences ISSN: 2517-9438 Vol:9, No:4, 2015

- [21] A. K. Bhattacharyya, "Effects of ground plane and dielectric truncations on the efficiency of a printed structure," IEEE Trans. Antennas Propagat., vol. 39, pp. 303-308, 1991.
- [22] Y. Murakami, I. Chiba, and Y. Karasawa, "Slot-coupled self-duplexing array antenna for mobile satellite communications," IEE Proc. Microw. Antennas Propagat., vol. 143, pp. 119–123, 1996.
- Antennas Propagat., vol. 143, pp. 119–123, 1996.
 [23] P. Brachat and J. M. Baracco, "Dual-polarization slot-coupled printed antennas fed by strip line," IEEE Trans. Antennas Propagat., vol. 43, pp.738–742, 1995.
- [24] M. Yamazaki, E. T. Rahardjo, and M. Haneishi, "Construction of a slotcoupled planar antenna for dual polarization," Electron. Lett., vol. 30, pp. 1814–1815, 1994.
- [25] B. G. Porter, L. L. Rauth, J. R. Mura, and S. S. Gearhart, "Dualpolarized slot-coupled patch antennas on duroid with teflon lenses for 76.5-GHz automotive radar systems," IEEE Trans. Antennas Propagat., vol. 47, pp. 1836–1842, 1999.
- [26] D. M. Pozar and S. D. Targonski, "Improved coupling for aperturecoupled microstrip antennas," Electron. Lett., vol. 27, no. 13, pp. 1129– 1131, 1991.
- [27] V. Rathi, G. Kumar, and K. P. Ray, "Improved coupling for aperture coupled microstrip antennas," IEEE Trans. Antennas Propagat., vol. 44, pp. 1196–1198, 1996.

Riki H Patel is currently pursuing the M.Tech in Electronic and communication Engineering (Communication system) from CSPIT, Changa & he had completed the B.Tech in Electronic and communication from CSPIT CHARUSAT.

Arpan Desai has received his M.Tech in Electronic and communication Engineering (Communication system) from CSPIT, Changa (2015) & M.S in Wireless communication from Brunel University, UK (2008). He has completed his BE (Electronics and communication) from Sardar Patel University in 2006. He is currently working as Assistant Professor in G.H.Patel College of Engineering and Technology, V.V.Nagar

Trushit Upadhyaya has received his B.E. Electronics and Communication Engineering - Gujarat University, Ahmadabad, Gujarat, India and M.E. from Telecommunications - Institute of Telecommunication Research, at University of South Australia, Adelaide, South Australia, He is currently pursuing his Ph.D in Antenna System Design for Satellite Communication - Charotar University of Science and Technology, Changa, Gujarat, India He is a member of Institute of Electrical and Electronics Engineers (IEEE) Engineers Australia (EA) Indian Society for Technical Education (ISTE).

Shobhit K. Patel was born in Gujarat, India, in 1984. He received the B.E. and M.E. degrees in electronics & communication engineering from the Gujarat University, India, in 2005 and 2008 respectively. He received the Ph.D. degree in electronics & communication engineering from Charotar University of Science & Technology, India, in 2014.

In 2007, he joined the Department of Electronics & Communication Engineering, Charotar University of Science & Technology, as an Assistant Professor, and in 2014 became an Associate Professor. His current research interests include RF and Microwave engineering, metamaterials, plasmonics, optics. Dr. Patel is an active member of many of the national and international academies. He was invited to deliver expert talks by many of the reputed institutions. He has published many papers in peer reviewed impact factor intenational journals and also presented papers in international conferences.