

# A Novel System of Two Coupled Equations for the Longitudinal Components of the Electromagnetic Field in a Waveguide

Arti Vaish and Harish Parthasarathy

**Abstract**—In this paper, a novel wave equation for electromagnetic waves in a medium having anisotropic permittivity has been derived with the help of Maxwell's curl equations. The  $x$  and  $y$  components of the Maxwell's equations are written with the permittivity ( $\epsilon$ ) being a  $3 \times 3$  symmetric matrix. These equations are solved for  $E_x$ ,  $E_y$ ,  $H_x$ ,  $H_y$  in terms of  $E_z$ ,  $H_z$ , and the partial derivatives. The  $Z$  components of the Maxwell's curl are then used to arrive to the generalized Helmholtz equations for  $E_z$  and  $H_z$ .

**Keywords**—Electromagnetism, Maxwell's Equations, Anisotropic permittivity, Wave equation, Matrix Equation, Permittivity tensor.

## I. INTRODUCTION

OVER the several decades, anisotropic materials have been extensively analysed and studied as they can successfully describe the real-world configurations. In addition to this, devices incorporating these materials acquire interesting directionally dependent properties which are useful in their operations [1]. In recent years, there have been increasing interests in the interactions between electromagnetic fields and anisotropic media [2]-[20]. Anisotropic medium has wide applications in the design and analysis of various novel antenna and microwave devices of high performance and utility [21] -[25]. With the advancement of the technology, the reconstruction of anisotropic constructive parameters and principal axis in three dimensional problem is of practical importance in microwave range. In the studies of Fedorov, and Borzdov, the direction of the principal axis of the anisotropic medium was obtained [24]-[27]. The idea of excluding the transverse components in favour of the longitudinal components of the electromagnetic field in a anisotropic medium has been applied, number of times, in connection with the anisotropic dielectric waveguide or optic fibres [28]-[38]. This work extends this idea for a more general model of a medium. In particular, a novel system of two coupled equations has been presented for the longitudinal components of the electromagnetic field in a waveguide filled with a homogeneous medium characterized by a general symmetric permittivity tensor.

## II. WAVE EQUATION WITH ANISOTROPIC PERMITTIVITY

The vector wave equation which describes the wave propagation along a rectangular waveguide with a nonhomogeneous

Arti Vaish is working as Assistant Professor with the Department of Electronics and Communication Engineering, Manav Rachna International University, Faridabad (Haryana), Email: vaisharti@gmail.com.

Professor Harish Parthasarathy is with the Statistical Signal Processing Group, Division of ECE, Netaji Subhash Institute of Technology, New Delhi.

cross section and anisotropic dielectric material may be obtained from the Maxwell equations. The fields are assumed to propagate in the  $Z$  direction and have a harmonic time dependence of the form  $e^{j\omega t - \gamma z}$  where  $\gamma = \alpha + j\beta$ , with  $\omega$ ,  $\alpha$  and  $\beta$  being the angular frequency, the attenuation constant and the phase constant, respectively. The magnetic permeability  $\mu$  is assumed to be constant and equal to the free space permeability, i.e.,  $\mu = \mu_0$ . The Maxwell equations are given as follow:

$$\nabla \times E = -j\omega\mu H \quad (1)$$

$$\nabla \times H = j\omega\epsilon E \quad (2)$$

where the electric and magnetic field vectors  $E$  and  $H$  are given by

$$E = E_x i + E_y j + E_z k, \quad (3)$$

$$H = H_x i + H_y j + H_z k. \quad (4)$$

Here  $i$ ,  $j$  and  $k$  are the unit vectors along the  $x$ ,  $y$  and  $z$  directions. The tensor permittivity  $\epsilon$  is given by,

$$\epsilon = \begin{pmatrix} \epsilon_{xx} & \epsilon_{xy} & \epsilon_{xz} \\ \epsilon_{yx} & \epsilon_{yy} & \epsilon_{yz} \\ \epsilon_{zx} & \epsilon_{zy} & \epsilon_{zz} \end{pmatrix} \quad (5)$$

Now expanding equation (1) and comparing the coefficients of  $i$ ,  $j$  and  $k$

$$\begin{pmatrix} i & j & k \\ \frac{\partial}{\partial x} & \frac{\partial}{\partial y} & \frac{\partial}{\partial z} \\ E_x & E_y & E_z \end{pmatrix} = -j\omega\mu(H_x i + H_y j + H_z k) \quad (6)$$

It can be written as follow:

$$\frac{\partial E_z}{\partial y} - \frac{\partial E_y}{\partial z} = -j\omega\mu H_x \quad \text{or} \quad E_{z,y} + \gamma E_y = -j\omega\mu H_x \quad (7)$$

$$\frac{\partial E_z}{\partial x} - \frac{\partial E_x}{\partial z} = j\omega\mu H_y \quad \text{or} \quad E_{z,x} + \gamma E_x = j\omega\mu H_y \quad (8)$$

$$\frac{\partial E_y}{\partial x} - \frac{\partial E_x}{\partial y} = -j\omega\mu H_z \quad \text{or} \quad E_{y,x} - E_{x,y} = -j\omega\mu H_z \quad (9)$$

where

$$\frac{\partial}{\partial z} = -\gamma \quad \text{and} \quad E_{i,j} = \frac{\partial E_i}{\partial j} \quad i, j = x, y, z$$

Similarly, from equation (2), we have

$$H_{z,y} + \gamma H_y = j\omega(\epsilon_{xx} E_x + \epsilon_{xy} E_y + \epsilon_{xz} E_z) \quad (10)$$

$$H_{z,x} + \gamma H_x = -j\omega(\epsilon_{yx}E_x + \epsilon_{yy}E_y + \epsilon_{yz}E_z) \quad (11)$$

$$H_{y,x} - H_{x,y} = j\omega(\epsilon_{zx}E_x + \epsilon_{zy}E_y + \epsilon_{zz}E_z) \quad (12)$$

After rearranging equations (7), (8), (10) and (11), we have:

$$\gamma E_y + j\omega\mu H_x = -E_{z,y} \quad (13)$$

$$\gamma E_x - j\omega\mu H_y = -E_{z,x} \quad (14)$$

$$j\omega\epsilon_{xx}E_x + j\omega\epsilon_{xy}E_y - \gamma H_y = H_{z,y} - j\omega\epsilon_{xz}E_z \quad (15)$$

$$j\omega\epsilon_{yx}E_x + j\omega\epsilon_{yy}E_y + \gamma H_x = -j\omega\epsilon_{yz}E_z - H_{z,x} \quad (16)$$

The above four equations can be written as a matrix equation for the variables  $E_x$ ,  $E_y$ ,  $H_x$  and  $H_y$  in terms of  $E_z$  and  $H_z$  and their partial derivatives as follow:

$$\begin{pmatrix} 0 & \gamma & j\omega\mu & 0 \\ \gamma & 0 & 0 & -j\omega\mu \\ j\omega\epsilon_{xx} & j\omega\epsilon_{xy} & 0 & -\gamma \\ j\omega\epsilon_{yx} & j\omega\epsilon_{yy} & \gamma & 0 \end{pmatrix} \begin{pmatrix} E_x \\ E_y \\ H_x \\ H_y \end{pmatrix} = \begin{pmatrix} -j\omega\epsilon_{yz}E_z - H_{z,x} - E_{z,y} \\ -E_{z,x} \\ H_{z,y} - j\omega\epsilon_{xz}E_z \\ -j\omega\epsilon_{yz}E_z - H_{z,x} \end{pmatrix} \quad (17)$$

Or

$$\begin{pmatrix} E_x \\ E_y \\ H_x \\ H_y \end{pmatrix} = \begin{pmatrix} 0 & \gamma & j\omega\mu & 0 \\ \gamma & 0 & 0 & -j\omega\mu \\ j\omega\epsilon_{xx} & j\omega\epsilon_{xy} & 0 & -\gamma \\ j\omega\epsilon_{yx} & j\omega\epsilon_{yy} & \gamma & 0 \end{pmatrix}^{-1} \begin{pmatrix} -j\omega\epsilon_{yz}E_z - H_{z,x} - E_{z,y} \\ -E_{z,x} \\ H_{z,y} - j\omega\epsilon_{xz}E_z \\ -j\omega\epsilon_{yz}E_z - H_{z,x} \end{pmatrix} \quad (18)$$

Letting  $A$  denote the coefficient matrix [39] and  $\Delta = |A|$ , we have

$$A^{-1} = \frac{C}{\Delta} = B \quad (19)$$

Now the determinant of matrix  $A$  is given by

$$\Delta = |A| = -\gamma^4 - \gamma^2\omega^2\mu(\epsilon_{xx} + \epsilon_{yy}) - \omega^4\mu^2(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \quad (20)$$

We write down explicit expression for all the matrix elements of  $B$

$$b_{ij} = \frac{(-1)^{i+j}D_{ji}}{\Delta} \quad (21)$$

Here,

$$\Delta = -\omega^4 \left[ \frac{1}{c^4} - \frac{\mu(\epsilon_{xx} + \epsilon_{yy})}{c^2} - \mu^2(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \right] = -\omega^4 k \quad (22)$$

$$k = \left[ \frac{1}{c^4} - \frac{\mu(\epsilon_{xx} + \epsilon_{yy})}{c^2} - \mu^2(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \right] \quad (23)$$

Here  $c$  is the speed of light and is equal to  $3 \times 10^8$  meter/second and  $k$  is an arbitrary constant. The solution to the transverse components of the electric and magnetic fields is given by

$$\begin{pmatrix} E_x \\ E_y \\ H_x \\ H_y \end{pmatrix} = B \begin{pmatrix} -j\omega\epsilon_{yz}E_z - H_{z,x} - E_{z,y} \\ -E_{z,x} \\ H_{z,y} - j\omega\epsilon_{xz}E_z \\ -j\omega\epsilon_{yz}E_z - H_{z,x} \end{pmatrix} \quad (24)$$

Now the components of matrix  $B$  and  $b_{ij}$  are given by

$$b_{[i=1-4, j=1]} = \begin{pmatrix} \omega^2\mu\gamma\epsilon_{xy} \\ -\gamma(\gamma^2 + \omega^2\mu\epsilon_{yy}) \\ j\omega\gamma^2\epsilon_{yy} + j\omega^3\mu(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \\ 0 \end{pmatrix}$$

$$b_{[i=1-4, j=2]} = \begin{pmatrix} -\gamma(\gamma^2 + \omega^2\mu\epsilon_{yy}) \\ \omega^2\mu\gamma\epsilon_{yx} \\ j\omega\gamma^2\epsilon_{yx} \\ -j\omega\gamma^2\epsilon_{xx} - j\omega^3\mu(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \end{pmatrix}$$

$$b_{[i=1-4, j=3,4]} = \begin{pmatrix} j\omega\mu(\gamma^2 + \omega^2\mu\epsilon_{yy}) & j\omega^3\mu^2\epsilon_{xy} \\ -j\omega^3\mu^2\epsilon_{yx} & j\omega\mu(\gamma^2 + \omega^2\mu\epsilon_{yy}) \\ \omega^2\mu\gamma\epsilon_{yx} & -\gamma(\gamma^2 + \omega^2\mu\epsilon_{xx}) \\ \gamma(\gamma^2 + \omega^2\mu\epsilon_{yy}) & -\omega^2\mu\gamma\epsilon_{xy} \end{pmatrix}$$

Now, with the help of above components and the equations 9 and 12, we get the following set of equations

$$\begin{aligned} & \gamma(\gamma^2 + \omega^2\mu\epsilon_{xx})\frac{\partial^2 E_z}{\partial x\partial y} - j\omega^2\mu\gamma\epsilon_{yx}\frac{\partial^2 E_z}{\partial x^2} - j\omega^3\mu^2\epsilon_{yx} \\ & \left( \frac{\partial^2 H_z}{\partial x\partial y} - j\omega\epsilon_{xz}\frac{\partial E_z}{\partial x} \right) - j\omega\mu(\gamma^2 + \omega^2\mu\epsilon_{xx}) \\ & \left( \frac{\partial^2 H_z}{\partial x^2} + j\omega\epsilon_{yz}\frac{\partial E_z}{\partial x} \right) + \omega^2\mu\epsilon_{xy}\frac{\partial^2 E_z}{\partial y^2} + \gamma(\gamma^2 + \omega^2\mu\epsilon_{yy}) \\ & \frac{\partial^2 E_z}{\partial y\partial x} - j\omega\mu(\gamma^2 + \omega^2\mu\epsilon_{yy}) \left( \frac{\partial^2 H_z}{\partial y^2} + j\omega\epsilon_{yz}\frac{\partial E_z}{\partial y} \right) \\ & - j\omega^3\mu\epsilon_{xy} \left( \frac{\partial^2 E_z}{\partial y\partial x} + j\omega\epsilon_{yz}\frac{\partial E_z}{\partial y} \right) = -j\omega\mu H_z \Delta \end{aligned} \quad (25)$$

$$\begin{aligned} & \omega^2\mu \left[ \frac{\partial H_z}{\partial x} (\epsilon_{zy}(\gamma^2 + \omega^2\mu\epsilon_{xx}) + \omega^2\mu\epsilon_{xy}\epsilon_{zx}) \right] + \\ & \omega^2\mu \left[ \frac{\partial H_z}{\partial y} (-\epsilon_{zx}(\gamma^2 + \omega^2\mu\epsilon_{yy}) + \mu\epsilon_{yx}\epsilon_{zy}) \right] + \\ & j\omega\gamma [\epsilon_{zy}(\gamma^2 + \omega^2\mu\epsilon_{xx}) - \omega^2\mu\epsilon_{xy}\epsilon_{zx}] \frac{\partial E_z}{\partial y} + j\omega E_z \\ & [\epsilon_{zz} + \omega^2\mu\epsilon_{zy}\epsilon_{yz}(\gamma^2 + \omega^2\mu\epsilon_{xx}) + \gamma^2\omega^2\mu\epsilon_{xz}\epsilon_{zx} + \\ & \omega^4\mu\epsilon_{zx}\epsilon_{yy}\epsilon_{xz}] = -j\omega\gamma^2\epsilon_{xx} - j\omega^3\mu(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx}) \\ & \frac{\partial^2 E_z}{\partial x^2} + \gamma(\gamma^2 + \omega^2\mu\epsilon_{yy})\frac{\partial^2 H_z}{\partial x\partial y} + \omega^2\mu\gamma\frac{\partial^2 H_z}{\partial x^2} \end{aligned}$$

$$\begin{aligned}
& +j\omega [\gamma^2\epsilon_{yy} + \omega^2\mu(\epsilon_{xx}\epsilon_{yy} - \epsilon_{xy}\epsilon_{yx})] \frac{\partial^2 E_z}{\partial y^2} + \\
& j\omega\gamma^2\epsilon_{yx} \frac{\partial^2 E_z}{\partial y\partial x} - \omega^2\mu\gamma\mu\epsilon_{yx} \frac{\partial^2 H_z}{\partial y^2} \\
& -\gamma(\gamma^2 + \omega^2\mu\epsilon_{xx}) \frac{\partial^2 H_z}{\partial y\partial x} - j\omega\gamma \\
& [\epsilon_{yz}(\gamma^2 + \omega^2\mu\epsilon_{xx}) - \omega^2\mu\epsilon_{yx}\epsilon_{xz}]
\end{aligned} \quad (26)$$

These are the two wave equations for a rectangular waveguide with anisotropic permittivity.

### III. CONCLUSION

We write down the  $x$  and  $y$  components of the Maxwell's equations

$$\nabla \times E = -j\omega\mu_0 H \quad (27)$$

And

$$\nabla \times H = j\omega\epsilon E \quad (28)$$

Where  $\epsilon$  is a  $3 \times 3$  symmetric matrix, given by,

$$\epsilon = \begin{pmatrix} \epsilon_{xx} & \epsilon_{xy} & \epsilon_{xz} \\ \epsilon_{yx} & \epsilon_{yy} & \epsilon_{yz} \\ \epsilon_{zx} & \epsilon_{zy} & \epsilon_{zz} \end{pmatrix} \quad (29)$$

We impose the condition that the fields depend on  $z$  as  $e^{j\omega t - \gamma z}$  where  $\gamma = \alpha + j\beta$ ,  $\omega$ ,  $\alpha$  and  $\beta$  being the angular frequency, the attenuation constant and the phase constant respectively. Then result is a set of four linear algebraic equations for  $E_x$ ,  $E_y$ ,  $H_x$ ,  $H_y$  in terms of  $E_z$ ,  $H_z$ ,  $E_{z,x}$ ,  $E_{z,y}$ ,  $H_{z,x}$  and  $H_{z,y}$ . These are solved yielding  $E_x$ ,  $E_y$ ,  $H_x$ ,  $H_y$  in terms of  $E_z$ ,  $H_z$ ,  $E_{z,x}$ ,  $E_{z,y}$ ,  $H_{z,x}$  and  $H_{z,y}$ . These expressions are then substituted into the  $z$  components of the  $\nabla \times E$  and  $\nabla \times H$  equations giving thereby a pair of second order coupled linear partial differential equations for  $(E_z, H_z)$ . It is to be noted that  $E_z$  or  $H_z$  can not be set to 0 because one of the pair of equations so obtained may not be satisfied. This is in contrast with the isotropic case.

### ACKNOWLEDGEMENTS

The authors gratefully acknowledges Prof. Raj Senani for his constant encouragement and Ar. Rajesh Ayodhyawasi for his support. Authors also gratefully acknowledge the authorities of Netaji Subhash Institute of Technology, New Delhi and Manav Rachna International University, Faridabad, Haryana for the provision of facilities for this research work.

### REFERENCES

- [1] C. A. Valagiannopoulos, On measuring the permittivity tensor of an anisotropic material from the transmission coefficients, Progress In Electromagnetics Research B, Vol. 9, 105116, 2008.
- [2] Wang, M.Y., J.Xu, J.Wu, B.Wei, H.L. Li, T.Xu, and D.B. Ge, FDTD study on wave propagation in layered structures with biaxial anisotropic metamaterials, Progress In Electromagnetics Research, PIER 81, 253-265, 2008.
- [3] Liu, S.-H., C.-H. Liang, W. Ding, L. Chen, and W.-T. Pan, Electromagnetic wave propagation through a slab waveguide, Progress In Electromagnetics Research M, PIER 76, 467-475, 2007.
- [4] Ding, W., L. Chen, and C.-H. Liang, Characteristics of electromagnetic wave propagation in biaxial anisotropic lefthanded materials, Progress In Electromagnetics Research, PIER 70, 3752, 2007.
- [5] Gong, Z. and G. Q. Zhu, FDTD analysis of an anisotropically coated missile, Progress In Electromagnetics Research, PIER 64, 6980, 2006.
- [6] Kristensson, G., S. Poulsen, and S. Rikte, Propagators and scattering of electromagnetic waves in planar bianisotropic slabs An application to frequency selective structures, Progress In Electromagnetics Research, PIER 48, 125, 2004.
- [7] Bass, F. and L. Resnick, The electromagnetic-wave propagation through a stratified inhomogeneous anisotropic medium, Progress In Electromagnetics Research, PIER 48, 6783, 2004.
- [8] A. Wexler, Computation of electromagnetic fields, IEEE Trans. Microwave Theory Tech., vol. MTT-17, pp. 416-439, Aug. 1969.
- [9] D. M. Pozar, Microwave Engineering, Reading, MA: Addison Wesley, 2004.
- [10] C. A. Balanis, Advanced Engineering Electromagnetics, New York: Wiley, 2005.
- [11] N. N. Rao, Elements of Engineering Electromagnetics, 3rd ed. New Jersey: Prentice Hall, 2002, p. 328.
- [12] W. H. Hayt, Engineering Electromagnetics, New York: McGraw- Hill, 2005, pp. 121, 184-192.
- [13] C. R. Paul and S. A. Nasar, Analysis of bi-anisotropic Pbg structure using plane wave expansion method, Progress In Electromagnetics Research, PIER 42, 233246, 2003.
- [14] Zheng, L. G. and W. X. Zhang, Higher-order numerical methods for transient wave equations, Springer, New York, 2002.
- [15] K. S. Yee, Numerical solution of initial boundary value problems involving Maxwell's equations isotropic media, IEEE Trans. Antennas Propagation, Vol. 14, no.5, pp.302-307, May 1966.
- [16] Zhang, M., L. W. Li, T. S. Yeo, and M. S. Leong, Scattering by a gyrotropic bianisotropic cylinder of arbitrary cross section: An analysis using generalized multipole technique, Progress In Electromagnetics Research, PIER 40, 315333, 2003.
- [17] Wei, B. and D. B. Ge, Scattering by a two-dimensional cavity filled with anisotropic medium, Waves in Random Media, Vol. 13, No. 4, 223240, 2003.
- [18] Chen, H. T., G. Q. Zhu, and S. Y. He, Using genetic algorithm to reduce the radar cross section of three-dimensional anisotropic impedance object, Progress In Electromagnetics Research B, Vol. 9, 231248, 2008.
- [19] Yang, L. L., D. B. Ge, and B. Wei, An equivalent anisotropic coating technique based on dyadic surface impedance boundary condition, Chinese Journal of Electronics, Vol. 14, No. 4, 712716, 2005.
- [20] Huang, P. K. and H. C. Yin, Equivalent currents on an anisotropic material backed by a metal surface and their relation, Journal of Systems Engineering and Electronics, Vol. 11, No. 4, 110, 2000.
- [21] Yin, H. C., Z. M. Chao, and Y. P. Xu, A new free-space method for measurement of electromagnetic parameters of biaxial materials at microwave frequencies, Microwave and Optical Technology Letters, Vol. 46, No. 1, 7278, Jul. 5, 2005.
- [22] Valagiannopoulos, C. A., On measuring the permittivity tensor of an anisotropic material from the transmission coefficients, Progress In Electromagnetics Research B, Vol. 9, 105116, 2008.
- [23] Chen, X., T. M. Grzegorzczuk, and J. A. Kong, Optimization approach to the retrieval of the constitutive parameters of slab of general bianisotropic medium, Progress In Electromagnetics Research, PIER 60, 118, 2006.
- [24] Fedorov, F. I., G. N. Borzdov, and L. M. Barkovskii, Operator for the indices of refraction of plane waves in dispersive anisotropic media, Journal of Applied Spectroscopy, Vol. 43, No. 4, 1176 1182, 1985.
- [25] Borzdov, G. N., An intrinsic tensor technique in Minkowski space with applications to boundary value problems, J. Math. Phys., Vol. 34, No. 7, 31623196, 1993.
- [26] Lijun Zhang and Shanjia Xu, Edge-element analysis of anisotropic waveguides with full permittivity and permeability matrices, International Journal of Infrared and Millimeter Waves, vol. 16, no.8 1995, Springer, New York.
- [27] G. N. Borzdov, L. M. Barkovskii and F. I. Fedorov, Generalized dielectric permittivity tensor Translated from Zhurnal Prikladnoi Spektroskopii, Generalized dielectric permittivity tensor Vol. 43, No. 3, pp. 488495, September, 1985.
- [28] M. Ohtaka, Analysis of the guided modes in the anisotropic dielectric rectangular waveguides, Trans. Inst. Electron. Commun. Eng. Japan, vol. 364-C, pp. 674-681, Oct. 1981.
- [29] Y. Xu and R.G. Bosisio, An efficient method for study of general bianisotropic waveguides, IEEE Trans. Microwave Th. Tech., vol. 43, pp. 873-879, Apr. 1995.
- [30] H.Y. Yang and P.L.E. Uslenghi, Planar bianisotropic waveguides, Radio Sci., vol. 28, pp. 919-927, Sept.-Oct. 1993.

- [31] J.L. Tsalamengas, Interaction of electromagnetic waves with general bianisotropic slabs, *IEEE Trans. Microwave Theory Tech.*, vol. 40, pp. 1870-1878, Oct. 1992.
- [32] Haruhito Noro and Tsuneyoshi Nakayama, A New Approach to Scalar and Semivector Mode Analysis of Optical Waveguides, *J. Lightwave Technol.*, Vol.14, No.6, pp.1546-1556, June 1996.
- [33] C. Angulo Barrios, V. R. Almedia, R. Panepucci, and M. Lipson, Electrooptic Modulation of Silicon-on- Insulator Submicrometer-Size Waveguide Devices, *J. Lightwave Technol.*, Vol.21, No.10, pp.2332-2339 Oct.2003.
- [34] Harish Parthasarathy, *Advanced Engineering Physics*, First Edition , Ane books, India, 2006.
- [35] M. Ohtaka, *Analysis of the guided modes in the anisotropic dielectric rectangular waveguides*, Trans. Inst. Electron. Commn. Eng. Japan, vol. 364-C, pp. 674-681, Oct. 1981.
- [36] Haruhito Noro and Tsuneyoshi Nakayama, *A New Approach to Scalar and Semivector Mode Analysis of Optical Waveguides*, J. Lightwave Technol., Vol.14, No.6, pp.1546-1556, June 1996.
- [37] C. Angulo Barrios, V. R. Almedia, R. Panepucci, and M. Lipson, *Electrooptic Modulation of Silicon-on- Insulator Submicrometer-Size Waveguide Devices*, J. Lightwave Technol., Vol.21, No.10, pp.2332-2339 Oct.2003.
- [38] R. C. Alferness, *Waveguide electrooptic modulators*, IEEE Trans. Microwave Theory Tech., vol. MTT-30, pp. 1121-1137, Aug. 1982.
- [39] Erwin Keryszig, *Advanced Engineering Mathematics*, 8<sup>th</sup> Ed. New York: Wiley, 2005.